

L1A

GPS Active Antenna

DESCRIPTION

The L1A is a high performance L1 GPS active antenna suited for applications requiring low noise and excellent gain. The product functions to specifications over the entire operational voltage and temperature range at a minimal current draw. The product includes high frequency selectivity to avoid interference with other nearby transmitters.

FEATURES

- Outstanding Noise Figure < 1dB
- Excellent Typical Gain of 33dB
- Wide Voltage Range of 3VDC to 16VDC
- Tiny Current Draw < 20mA
- Bottom or Pole Mount
- Multiple Connector Options

OPTIONS

The L1A comes with many available options to meet specific needs. Please contact GPS Source via phone, email, or visit the website for further information on product options and specifications.



1 L1A Specifications

Table 1-1. Electrical Specifications

Operating Temperature -40°C to 85°C

Parameter		Conditions	Min	Тур	Max	Units	
Frequency Range (Passband)		Ant: Output, VDC = 3V to 16V, Output = 50Ω		1575	1590	MHz	
Out Impedance				50		Ω	
Gain	Element	Ant Element		3	3.5	dBiC	
	LNA	LNA, VDC = 3V to 16V, Output = 50Ω	32	33	35	dB	
Output SWR		VDC = 3V to 16V, Output = 50Ω			2.5:1	—	
Noise Figure		VDC = 3V to 16V, Output = 50Ω		0.8	1	dB	
Required DC Input Voltage		DC Input on RF Output Center Conductor	3		16	VDC	
LNA Current		Output = 50Ω, 5V		17	20	mA	
Rejection	+/-50MHz > 24dB	Ant: Output, VDC = 3V to 16V, Output = 50Ω	-22	-24	-25	dB	
	+/-100MHz > 35dB	Ant. Output, $VDC = 5V$ to $10V$, Output = 5022	-34	-35	-37		
Polarization		Right Hand Circular					

Page 2 of 7



2 Performance Data

2.1 Far Field Patterns — 1575MHz







Figure 2-2. Far Field Plots Azimuth Cuts





L1A Data Sheet 059-FAN-AAQ-XCX-RXZ-006 01/15/2020 Page 3 of 7

2.2 LNA Frequency Response





Note: Frequency selectivity of antenna element adds additional out of band rejection.

Page 4 of 7

GPSS-Sales@gd-ms.com www.gpssource.com L1A Data Sheet 059-FAN-AAQ-XCX-RXZ-006 01/15/2020



3 Product Options

Table 3-1. L1A Available Options

Available Options								
Power Source Voltage	Voltage Input		Туре					
Fower Source voltage	DC 3VDC to 16VDC		Input on Center pin of RF Connector.					
	Туре		Limitations					
	Ν	Female	N/A					
RF Connector	SMA	Female Male	N/A					
	TNC	Female	N/A					
RF Mounting	L Bracket Pole Mount Hardware		See Figure 3-1.					

Figure 3-1. L Bracket Pole Mount Hardware



4 Product Code Decoder



Notes: 1. Contact GPS Source for additional connector options.

- 2. This product is available only in black.
- 3. To have product/part codes customized to meet exact needs, contact GPS Source at GPSS-Sales@gd-ms.com or visit the website at www.gpssource.com.



Page 5 of 7

5 Mechanical Drawing

5.1 L1A GPS Active Antenna









L1A Data Sheet 059-FAN-AAQ-XCX-RXZ-006 Page 7 of 7, 01/15/2020 2121 Executive Cir., Ste 100 Colorado Springs, CO 80906 Phone: (+1)(719) 421.7300 Toll Free: (+1)(866) 289.4777 GPSS-Sales@gd-ms.com www.gpssource.com

У in

AS9100 and ISO 9001 Compliant Company

© 2014 GPS Source, Inc. All rights reserved.

GPS Source, Inc., GPS Live Inside, GPS Source logo, and other GPS Source, Inc. products, brands, and trademarks mentioned in this document are property of GPS Source, Inc. and/or its affiliates in the United States and/or other countries. Other products, brands, and trademarks are property of their respective owners/companies. Any rights not expressly granted herein are reserved.

DISCLAIMER: The materials in this document could include inaccuracies or typographical errors and are subject to change at any time. The materials are provided "as is" without warranty of any kind. To the maximum extent permitted by applicable law, GPS Source, Inc. and its suppliers hereby disclaim all warranties, either expressed or implied, and conditions with respect to the materials, their quality, performance, suitability, merchantability, fitness for a particular purpose, title, and non-infringement. LIMITATION OF LIABILITY: IN NO EVENT WILL GPS SOURCE, INC. AND ITS SUPPLIERS BE LIABLE FOR INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, WHETHER IN AN ACTION OF CONTRACT OR TORT, ARISING OUT OF THE USE OR INABILITY TO USE THE MATERIALS AVAILABLE IN THIS DOCUMENT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN PARTICULAR AND WITHOUT LIMITATION, GPS SOURCE, INC. SHALL HAVE NO LIABILITY FOR ANY LOSS OF USE, DATA, INCLUDING THE COSTS OF RECOVERING SUCH DATA, OR PROFITS.